

Reg No.: _____

Name: _____

APJ ABDUL KALAM TECHNOLOGICAL UNIVERSITY
FIFTH SEMESTER B.TECH DEGREE EXAMINATION(R&S), DECEMBER 2019

Course Code: EE311

Course Name: ELECTRICAL DRIVES & CONTROL FOR AUTOMATION

Max. Marks: 100

Duration: 3 Hours

PART A

Answer any three full questions, each carries 10 marks.

Marks

- | | | |
|---|--|-----|
| 1 | a) Explain how the OCC of a dc shunt generator is obtained. Define critical resistance and critical speed. | (6) |
| | b) List out the applications of dc generator | (4) |
| 2 | a) What are the various losses occurring in a dc generator | (4) |
| | b) In a 120V compound generator, the resistance of the armature, shunt and series windings are 0.06Ω , $25\ \Omega$ and $0.04\ \Omega$ respectively. The load current is 100 A at 120V. Find the induced emf and armature current when the machine is connected as long shunt | (3) |
| | c) What is mean by armature reaction? What are its effects on main field flux | (3) |
| 3 | a) Explain how the speed is related to flux and back emf for a series and shunt motor | (4) |
| | b) With the help of block diagram explain the power stages of dc motor | (4) |
| | c) A 250 V shunt motor on no load runs at 1000 rpm and takes 5 amperes .Armature and shunt field resistances are 0.2 and $250\ \Omega$ respectively. Calculate the speed when loaded taking a current of 50 A. The armature reaction weakens the field by 3% | (2) |
| 4 | a) Explain the working of a 3 point starter | (6) |
| | b) Explain the procedure for determining the efficiency of a dc motor | (4) |

PART B

Answer any three full questions, each carries 10 marks.

- | | | |
|---|--|-----|
| 5 | a) Derive the EMF equation of a transformer | (4) |
| | b) Explain the vector diagram of transformer under no load | (6) |

- 6 a) Draw and explain Instruments transformers (6)
b) Define voltage regulation of a transformer (4)
- 7 a) With a diagram explain the working principle of a 3 phase induction motor (6)
b) Draw the equivalent circuit of three phase induction motor (2)
c) A 3 phase Induction motor is wound for a 4 poles and is supplied from 50 Hz system calculate i) synchronous speed ii) speed of the rotor when the slip is 4% (2)
- 8 a) Explain the no load and blocked rotor test of a 3 phase induction motor (6)
b) A 4 pole 50 Hz 3phase induction motor has a rotor resistance of $0.024 \Omega/\text{ph}$ and standstill reactance of $0.6 \Omega/\text{ph}$. Determine the speed at which maximum torque is developed (4)

PART C

Answer any four full questions, each carries 10 marks.

- 9 a) Explain the working of a universal motor? (4)
b) Explain the constructional details of alternator (6)
- 10 a) Derive emf equation of an alternator (6)
b) Define voltage regulation of an alternator (4)
- 11 a) Explain the different starting methods of synchronous motor (6)
b) Find the number of armature conductors in series per phase required for the armature of a 3 phase , 50 Hz ,10 pole alternator . The winding is star connected to give a line voltage of 11 kV. The flux /pole is 0.16 Wb. Assume $K_c=1$ and $K_d=0.96$ (4)
- 12 a) Explain with figure the working of multistack variable reluctance stepper motor (6)
b) List out the advantages of variable reluctance motor (4)
- 13 a) With the help of neat diagram explain the working of hybrid stepper motor (6)
b) Draw and explain the torque speed characteristics of stepper motor (4)
- 14 a) List out the applications of stepper motors (4)
b) With block diagram explain programmable logic controllers (6)
